

Connect Carlson BRx6 with Collector App

## 1. Connect with wifi to the Brx6

<b>%</b>	D181228543018 Geen internet, open	
	<u>Eigenschappen</u>	
		Verbinding verbreken

2. In the internet explorer go to.

## http://192.168.10.1/

3. Use the following username en password (admin/s321)

Carlson.	BRx6+(NA)	Wachtwoord opslaan? Gebruikersnaam admin	×	T		
Status Information Download Management		Wachtwoord 5321 - Opsiaan N	Nooit			
<ul> <li>System Mode: Rover</li> <li>Longitude: 0.00000000 *</li> <li>Height: 0.000 m</li> <li>Satellites: 0</li> </ul>	- Current Datalink: UHF - Latitude: 0.0000000 * - Status: Idle - PDOP: 0.000 - TDOP: 0.000 - VRMS: 0.000 m	Wachtwoorden worden in je Google-account opgeslagen, zodat je deze op elk apparaat kunt gebruiken				
HDOP: 0.000     HRMS: 0.000 m     GNSS Time: 1980-01-06 08:00:00				_		
support@carlsonsw.com © Copyright 2013 Carlson Software. All Rights Reserved.						

4. Select settings in de webconfiguration and turn on the NMEA Message (GGA,GSA,GST)

Settin	gs workin	g mode	Device Con	mgu		EA Messi	age Satelli	les
GGA:	1Hz y	ZDA:	Off	٠	GEDOP:	Off	•	
GSA:	1Hz y	GSV:	Off	۳	GEREF:	Off	•	
GST:	1Hz y	VTG:	Off	٣	GESNR:	Off	•	
RMC:	Off	GLL:	Off	٣	GEVCV:	Off	•	
BIN3:	Off	BIN5:	Off	٣	GELBD:	Off	•	
ts							Save	Cancel

5. Press save and connect the Brx6 to the collector app.



 Open the collector app and go to settings -> Location -> Add receiver and select the Brx6 (D181228543018)

	GPS Receivers
Collection Location	Current
Location accuracy Set required location accuracy for data collect	CT D181228543018 Antenna Height 0.00 m
30 Feet	Other
Accuracy report Report location accuracy using a higher prob 95% confidence	Antenna Height 0.00 m
Location profile Control transformation of locations from GNS Default	
Location provider Current source used to collect location inform D181228543018 Antenna Height 0.00 m	+ Add a receiver
	Close

7. Choose the map in the Collector app and start collection data

