Installation instructions for the Enfora Registry Files

CINGULAR Wireless

This workflow explains how to copy a Cingular Wireless registry file into the Carlson Explorer. After this registry file is copied, all you will need to do is enter a username and password for Cingular. This procedure avoids having to type in several dialing property details, and avoids having to use the BVRP Pocket Phone Tools program.

Install the Registry file:

- 1. Copy the file called CINGULAR.REG from your PC to the SystemCF of the Explorer. Remember where you copied to, because you will need to browse for it once you enter the Registry Editor.
- 2. Go to the Start Menu and hit 'Run'



3. At the run prompt type 'regedit' and hit 'OK' The RegEdit interface is a critical level of programming for the device. DO NOT ATTEMPT ANY OTHER STEPS.

		🔺 🧟 🛃
	Run	×
	-	Type the name of a program, folder, or document, and Windows will open it for you.
4	<u>O</u> pen:	regedit
		OK Cancel <u>B</u> rowse

4. At the File menu click 'Import'

<u>F</u> ile	<u>E</u> dit	ab	ab Cd	123			?	×
Imp	ort C	itrl+0					 _	_
Ехр	ort C	trl+S			Edit	Del		
E <u>x</u> it	Ą	\lt+X				20.		
								_
I								

5. Browse for the 'CINGULAR.REG' File and then click OK

<u>File</u> <u>E</u>dit ab ab ab 123	? ×
Open 🗈 🥂 🧱 🏢	? ок 🗵
SystemCF	
 Bluetooth Carlson Utilities CINGULAR Data Geodetics Settings 	
<u>N</u> ame: CINGULAR <u>T</u> ype: Re	gistry Files (*.r 💌

- 6. Press the X button in the upper right to exit out of the RegEdit interface.
- 7. Insert the Enfora GSM CF card into the Explorer and Warm Boot. Warm Boot by going to Start Programs Tools Warm Boot.

Connect to the Internet:

1. Go to Start – Settings – Network and Dial-up Connections



2. Then double tap the Cingular Icon.

Connectio	? ×		
-	<u> 7</u>	21	5
Make New Connection	T-Mobile US	Cingular	PC-115K
USB_Serial			
USB_Serial			

3. Enter User Name: <u>WAP@CINGULARGPRS.COM</u>. Password: CINGULAR1 Then Press the Connect button.

Conn	Dial-Up Connection 🛛 🛛 🗙		?	×
Make N Connec USB_S	Cingular User Name: WAP@CINGULARGPR Password: ************************************		K	
	Phone: Dial from: Cell Dial Properties	[

4. After pressing the Connect button the following messages will occur. If the connection is successful, the "Connected" message will be displayed.

Opening Port Dialing *99***1# User Authenticated Device Connected Connected

Conne	ection	≞	< 😰			?	×
-		3 7		3 ,1			
Make N	Cingula	ar Statu	s		×	к	
Connec	2	_					
- 😒	21	Open	ing Po	ort			
USB_S	Hide t	his messa	ige:	Hid	e		
	Cancel	connect	ion:	Cano	:el		

Conne	ection 🚦 🗙 🖻	1	? ×
-	🦻 🕽	3 7	
Make M	Cingular Status		×ĸ
Connec	Dialing '*99	9***1#'	
USB_9	Hide this message:	Hide	
	Cancel connection:	Cancel	

Conne	ection 📇 🗙 🖆		? ×
-] 🛃 🕄	<u>\$</u> 7	
Make N	Cingular Status		×ĸ
Connec	🛃 User Authe	enticated	
USB_9	Hide this message:	Hide	
	Cancel connection:	Cancel	

Conne	ection		7	?	×
		<u>3</u>	3 7		
Make M	Cingula	r Status		×ĸ	
Connec	2 0	Douico Co	opported		
	ĽĽ	Device Cl	Jrinecteu		
USB_S	Hide th	is message:	Hi	te	
	Cancel	connection:	Car	icel	

